



# EazyVolt Pro LED

## 2-pole voltage tester

Art. number: 626002030

The EazyVolt Pro LED is a reliable and safe 7-in-1 automatic voltage tester up to 690 V, with the following functions:



- Measuring AC voltage
- Measuring DC voltage
- Phase detection (1-pole)
- Continuity
- Phase rotation
- Selftest
- Torch

### Features

- Fully automatic
- Audible sound
- Torch by ultra bright LED
- Selectable probe tips 2 - 4 mm
- Side indication
- Water resistance (IP65)
- Fail safe (no battery needed for VAC/DC measurements)
- Shuko power outlet compliant (19 mm)
- 3-phase rotation
- 1-hand operation



### Specifications

#### Functions

|            |                |
|------------|----------------|
| Voltage    | 6...690 VAC/DC |
| Continuity | < 500 kΩ       |
| Frequency  | 16...800 Hz    |

#### General

|                         |   |
|-------------------------|---|
| Auto power on           | > 6 VAC/DC  |
| LED resolution          | 6, 12, 24, 50, 120, 230, 400, 690 V   |
| Voltage detection       | Automatic   |
| Response time           | <1 s  |
| IP class                | IP65  |
| Overprotection category | CAT III 600 V / CAT II 690 V  |
| Drop proof              | 1 meter   |
| Standards               | EN 61010-1 /-031, EN 61243-3, EN 60529, EN 61557-7 /-10 /-1, EN 61326, EN 55011 |
| Approvals               | CE, TUV, GS   |
| Supply                  | 2x 1.5 V AAA batteries  |
| Dimensions              | 280 x 74 x 34 mm  |
| Weight                  | 220 g (incl. batteries)   |
| Including               | Batteries, manual   |